## **2000 Surge Watts**

## SPORTSMAN

## Portable Cenerator

## 1400 Running Watts

Dual Fuel Gasoline or Propane Powered



- 2000 Surge Watts / 1400 Running Watts\*
- 4-Stroke OHV Engine 94cc
- Recoil Start
- 3.5 HP Dual Fuel Engine
- 1 12V D/C Outlet
- 2 120V A/C Outlets
- Engine Run Time: 9 Hours @ 50% Load
- Runs 12 hours @ 50% Load on 20 lbs of LPG Fuel
- (Propane Tank Not Included)

- Low Oil Shutdown
- · EPA Approved
- Noise Level: 68dB @ 0% Load
- · Oil Capacity: 12.0 ounces
- Fuel Capacity: 1.2 gallon
- Fuel Type: Unleaded Gasoline Only 87 rating or higher
- 3,600 RPM
- Mobility Kit Not Available
- \* SURGE WATTS / RUNNING WATTS MAY BE REDUCED BY 10% WHEN USING PROPANE FUEL VS USING GAS

Item No.	UPC No.	Case Wt.	Lbs. Cubic Ft.	Case Qty.	
GEN2000DF	0 27077 07974	6 55.0	2.2	1	
950 Hoff Road	O'Fallon, I	MO 63366	Phone 636.532.988	88 Fax 63	86.537.1055