4000 Surge Watts

SPORTSMAN

Portable Cenerator

3500 Running Watts

Dual Fuel Gasoline or Propane Powered



- 4000 Surge Watts / 3500 Running Watts*
- 4-Stroke OHV Engine 212cc
- Recoil Start
- 7.0 HP Gasoline Engine
- 1 12V D/C Outlet
- 4 120V A/C Outlets
- 1 120V RV Outlet
- Engine Run Time: 10 Hours @ 50% Load
- Runs 12 hours @ 50% Load on 20 lbs of LPG Fuel
- (Propane Tank Not Included)

- Low Oil Shutdown
- AVR Automatic Voltage Regulation
- EPA Approved
- Noise Level: 69dB @ 0% Load
- · Oil Capacity: 20 ounces
- Fuel Capacity: 3.9 gallon
- Fuel Type: Unleaded Gasoline Only Octane rating 87 or higher
- 3,600 RPM
- Mobility Kit : Available Separately
- * SURGE WATTS / RUNNING WATTS MAY BE REDUCED BY 10% WHEN USING PROPANE FUEL VS USING GAS

Item No.	UPC No.	Case Wt.	Lbs.	Cubic Ft.	Case Qty.	
GEN4000DF-SS	0 27077 0823	5 7 102.	.0	5.34	1	
950 Hoff Road	O'Fallon, N	//O 63366	Phone	636.532.9888	Fax 636.5	537.1055